ARK IN THE PARK SEEDFALL COLLECTION METHODS



<u>Field Gear:</u>	Methods: AT BASE
☐ Kauri kit (trigene, brush)	1. Fill in intentions book
Repair kit + hammer	2. Collect all gear + record radio & beacon #
(Blue + orange tape & white $oldsymbol{\Delta}$)	3. Number collection labels before leaving base
Gloves – latex or gardening	
☐ Line clearing gear (secateurs/saw, safety	Methods: IN FIELD
glasses)	1. Navigate to line start
Compass (optional)	2. Refresh triangles & flagging tape if needed
☐ Hand sanitiser	3. Remove any large sticks from funnel, then push
Charged mobile phone (optional)	seeds/leaves into funnel & stocking
	4. Remove wire & PVC pipe from below funnel
☐ Radio – charged + locator beacon	5. Hold stocking securely & gently push all
First aid kit	leaves/seeds deeper into stocking, then
Outdoor clothes & boots	remove stocking
Spare warm clothes + rain gear	If leaves/seeds don't fit in one sticking, put
☐ Food & water	extra into spare new stocking
	7. Place completed collection labelinto stocking,
Monitoring Gear:	then tie a knot in top of stocking
☐ Monitoring line description + map	8. Attach new stocking, replace rubber band if
Spare wires (2-3)	needed. Rubber band should sit between tabs
Spare rubber bands (5-10)	at bottom of funnel and holes for wire
	9. Place PVC pipe over new stocking & secure
☐ Collection labels (1 per station)	with wire
Stockings (1 per station + spares)	10. Return to base, do kauri dieback cleaning,
Pencil	hang stockings from line in storeroom (please
	DON'T tie stockings to line - use clothes pegs)
*If kits are already made, these will have the correct	11. Sign out of intentions book + leave any
number of each item +1 as a spare, i.e. 15 labels for 14 stations	maintenance notes for staff

Health and Safety:

<u>Key hazards:</u> field work (intentions book, radio & locator beacon, first aid kit, map), rough terrain (boots + awareness of surroundings), sharp wire (gardening gloves)

Phone numbers: Ark office 09 810 7014, Ranger station 09 810 8133, Arataki Visitor Centre 09 892 4789

Radio channels: 5 = line of sight 1, 2, 3, 4 = open channels for Waitākere Ranges & Arataki Visitor Centre

Last update: 23 August 2021







Above: Full funnel set up

Right:

- Wire securing PVC pipe (steps 4 & 9)
- Moving PVC pipe without dislodging stocking (steps 4 & 9)
- Funnel base with stocking secured by rubber band (steps 5 & 8)



Site name

Station ID

Date put out

Date collected

Collector name

Comments

Site name: Cascades

Station ID: CKP##

<u>Date put out:</u> month year

<u>Date collected:</u> today's date dd/mm/yy

<u>Collector name:</u> your name

Comments: Any abnormalities

